



Stabilizer Power REG 1.000 VA

- 1 - On/Off switch
- 2 - Led AVR/Power
- 3 - AC input cable
- 4 - Input fuse
- 5 - Stabilized output socket
- 6 - RJ11 port



Stabilizer Power REG 2.000 VA



Stabilizer Power REG 3.000 VA

- 1 - On/Off switch
- 2 - Input Voltage Display
- 3 - Output Voltage Display
- 4 - Start Up Delay time selector stabilization function: Delay 3 minutes, Undelay 10 seconds.
- 5 - Input Voltage range selector
- 6 - Led Power - AVR - Overvoltage/undervoltage
- 7 - AC input cable
- 8 - Stabilized output socket
- 9 - Input socket

Main Specifications

- Domestic users, Lighting Systems, Industrial Processes, Communications, Electromedical equipment
- High stabilization speed
- High Efficiency
- No brownouts stabilization
- Do not introduce harmonic distortion
- Management changes from 0 to 100% load

Specifications

Model	STABILIZER POWER REG 1.000-2.000-3.000		
	FSTELPRE1000M	FSTELPRE2000M	FSTELPRE3000M
Code	FSTELPRE1000M	FSTELPRE2000M	FSTELPRE3000M
Nominal Power	1.000 VA	2.000 VA	3.000 VA
Active Power	800 W	1.600 W	2.400 W
Power Factor	0,8		
Technology	Electronic stabilization		
Start Up Delay time selector stabilization function	-	Selectable 3 minutes-10 seconds	
Telephone/modem protection	RJ11		
Dimension WxHxD	16,1x8,6x16,6 cm	13x18x24 cm	15x20x30 cm
Dimension (with packing) WxHxD	19,1x11,9x23,1 cm	19x24x39 cm	23x27x33 cm
Weight	2 Kg	6,6Kg	8,6 Kg
Input			
Number of phases	1Ph+N		
Nominal voltage	230Vac		
Input voltage range	180Vac-264 Vac	110Vac-280Vac o 150Vac-270Vac (selezionabile)	
Nominal frequency	50 Hz	50/60 Hz	
Output			
Number of phases	1F+N		
Nominal voltage	230Vac		
Voltage regulation	±6%		
Nominal frequency	50 Hz	50/60 Hz	
Environmental specification			
Working temperature	From 0 to 40 °C		
Humidity	< 95% without condensation		
Maximum altitude	3000 m		
IP protection	IP20		
Certifications	CE		
Warranty			
Standard	24 months - After registration on www.tecnoware.com		

© 2018 Tecnoware Power Systems. The technical data may change without prior notice.